

Mega Bar LED™ DMX Values and Functions - 7 Channels

Channel	Value	Function
1	0 - 255	RED 0% → 100%
2	0 - 255	GREEN 0% → 100%
3	0 - 255	BLUE 0% → 100%
4	0 - 14 15 - 28 29 - 42 43 - 56 57 - 70 71 - 84 85 - 98 99 - 112 113 - 126 127 - 140 141 - 154 155 - 168 169 - 182 183 - 196 197 - 210 211 - 224 225 - 238 239 - 255	<u>MACROS/PROGRAMS</u> OFF RED YELLOW GREEN CYAN BLUE PURPLE WHITE COLOR CHANGE COLOR FLOW COLOR DREAM MULTI COLOR DREAM FLOW 2 COLOR FLOW COLOR CHANGE FADE COLOR FLOW FADE 2 COLOR FLOW FADE SOUND ACTIVE
5	0 - 255	<u>SPEED/SOUND SENSITIVITY CONTROL*</u> SLOW → FAST
6	0 1 - 255	<u>STROBE</u> OFF SLOW → FAST
7	0 1 - 255	<u>DIMMER</u> OFF 0 → 100%