

## ZerOS Software Release (Public Release)

Released Version:	7.9.1	Release Date:	21 <sup>st</sup> October 2016
Previous Versions:	7.9	Release Date:	8 <sup>th</sup> July 2016

## ZerOS 7.9.1 Software Release

### Introduction

Release 7.9.1 of ZerOS is a critical software replacement for 7.9, recommended for all consoles and servers running the ZerOS Operating System (listed below).

ZerOS 7.9.1 replaces ZerOS 7.9 and does not provide any additional features or enhancements. For descriptions of new features and enhancements added in ZerOS 7.9, please reference the ZerOS 7.9 release notes.

### Products Affected

- ✓ FLX
- ✓ ORB Series
- ✓ SCD Server Pro
- ✓ Phantom ZerOS (offline software)

### Compatibility

No compatibility issues known from 7.9.

### Update Instructions

Please carefully follow the update instructions available at the end of this document.

The software installation process completely removes all data on the console, including any current show files. If the current show file is still required, **please ensure that backups are taken before proceeding with the update.** After completing the update you may re-load your show if required.

When performing a software update it is important to ensure that the power supply to your desk is stable and reliable. Power loss during a software update can render your desk unusable.

### Known issues

No known issues.

## Software Update Instructions

### Introduction

Please familiarise yourself with these update instructions before proceeding. Instructions must be followed accurately and in order. Deviations or omissions could render the desk unusable and require it to be returned to the factory for recovery.

If any difficulties are encountered at any point, or you are in doubt on any of the instructions below, then do not proceed any further with the update and contact Zero 88 for assistance.

The software installation process completely removes all data on the console, including any current show files. If the current show file is still required, **please ensure that backups are taken before proceeding with the update**. After completing the update you may re-load your show if required.

When performing a software update it is important to ensure that the power supply to your desk is stable and reliable. Power loss during a software update can render your desk unusable.

### Consoles running ZerOS 7.8.3 or later.

To perform the update:

- Download the software from the Zero 88 website ( [zero88.com/software/zeros](http://zero88.com/software/zeros) )
- Unzip the download and save the .exe file onto a USB stick (don't put it inside any folders)
- Plug the USB stick into your console
- Press SETUP to enter the console's setup screen and choose "Load file" on the monitor
- Select the file from the list displayed on screen and follow the onscreen instructions
- Once the update is complete, remove the USB Memory Stick and reboot the desk

Once all the software is up to date, you can get on with enjoying the new features in the desk software. Zero 88 recommend printing these Release Notes and having them with you when operating the desk, as some functionality may have changed which is explained in these notes.

### Consoles running ZerOS 7.8.2.39 or older.

To perform the update, you will need a USB Memory Stick, which will be erased and formatted as part of the process. Make sure you first backup any data on the USB Memory Stick that you wish to keep.

Some types of USB Memory Stick may not be bootable by the desk. If you experience any difficulties then try using the Zero 88 USB Memory Stick supplied with the desk.

The update will reinstall all the software on the desk. An .exe file (USB Install Creator application) is run on a Windows PC to create a bootable USB Memory Stick.

Download the USB Install Creator application from the Zero 88 website (<http://www.zero88.com/software/zeros>) and, after unzipping, run it. Insert a USB Memory Stick into your Windows PC when prompted and follow the on screen instructions of the USB Install Creator. After a few minutes, the install creator will instruct you to remove the USB Memory Stick, which now contains the update for the desk.

Remove the USB Memory Stick from your PC and insert it in one of the desks USB ports. Power on the desk and the desk will automatically boot into the software update application. It is recommended that you have a monitor, keyboard and mouse connected to the desk to perform this update. Press the [Install ZerOS] button on the monitor and the software will be installed.

Once the update is complete, you can remove the USB Memory Stick and reboot the desk. At this point your desk contains the latest software.