

64B LED PRO DMX Values and Functions - 7 Channel

Channel	Value	Function
1	0 - 255	RED 0% → 100%
2	0 - 255	GREEN 0% → 100%
3	0 - 255	BLUE 0% → 100%
4	0 - 7 8 - 255	NOTHING COLOR MACRO
5	0 - 15 16 - 255	NOTHING STROBING/MACRO SPEED
6	0 - 31 32 - 63 64 - 95 96 - 127 128 - 159 160 - 191 192 - 223 224 - 255	NOTHING DIM → BRIGHT BRIGHT → DIM DIM → BRIGHT → DIM COLOR MIXING 3 COLOR CHANGE 7 COLOR CHANGE SOUND ACTIVE
7	0 - 255	DIMMER 0% → 100%