



Triggers



•


DMX In



MIDI Show Control



OSC Examples



1st	2nd	3rd
/zeros /flx /lighting /lx	/cue	/go
	/q	/pause
		/next
	/playback	/go
	/pb	/pause
		/level
		/release
		/view
	/blackout	
	/bo	
/dbo		
/grandmaster		/level
/gm		(can be omitted)
/macro		

Go

	String	Combined	Argument (with or without quotes)
Go Playback X Cue Y	/zeros/cue/go/X/Y	/zeros/cue/go/X "Y"	/zeros/cue/go "X", "Y" /zeros/cue/go "X/Y"
Go Cue Y (current playback)	/zeros/cue/go/Y		/zeros/cue/go "Y"
Go (current playback)	/zeros/cue/go		

Pause

	String	Combined	Argument (with or without quotes)
Pause (current playback)	/zeros/cue/pause		

Next

	String	Combined	Argument (with or without quotes)
"Next" Playback X Cue Y	/zeros/cue/next/X/Y	/zeros/cue/next/X "Y"	/zeros/cue/next "X", "Y" /zeros/cue/next "X/Y"
"Next" Cue Y (current playback)	/zeros/cue/next/Y		/zeros/cue/next "Y"

Go

	String	Combined	Argument (with or without quotes)
Go Playback X	/zeros/playback/go/X		/zeros/playback/go "X"
Go (current playback)	/zeros/playback/go		

Pause

	String	Combined	Argument (with or without quotes)
Pause Playback X	/zeros/playback/pause/X		/zeros/playback/pause "X"
Pause (current playback)	/zeros/playback/pause		

Playback levels

	String	Combined	Argument (with or without quotes)
Playback X to level Y% over Z seconds	/zeros/playback/level/X/Y /zeros/playback/level/X/Y/Z	/zeros/playback/level/X "Y" /zeros/playback/level/X/Y "Z" /zeros/playback/level/X "Y", "Z" /zeros/playback/level/X "Y/Z"	/zeros/playback/level "X", "Y" /zeros/playback/level "X/Y" /zeros/playback/level "X", "Y", "Z" /zeros/playback/level "X/Y/Z"
<i>Level in %. Optional fade time, in seconds If fade time is not set, ZerOS will use the raise/lower time ("move" rather than "fade")</i>			

Release

	String	Combined	Argument (with or without quotes)
Release Playback X	/zeros/playback/release/X		/zeros/playback/release "X"
Release (current playback)	/zeros/playback /release		

View


	String	Combined	Argument (with or without quotes)
View Playback X	/zeros/playback/view/X		/zeros/playback/view "X"

	String	Combined	Argument (with or without quotes)
Run User Macro X	/zeros/macro/X		/zeros/macro "X"
Grand Master to level Y% over Z seconds	/zeros/grandmaster/level/Y /zeros/grandmaster/level/Y/Z	/zeros/grandmaster/level/Y "Z"	/zeros/grandmaster/level/ "Y" /zeros/grandmaster/level "Y", "Z"
	/zeros/grandmaster/Y /zeros/grandmaster/Y/Z	/zeros/grandmaster/Y "Z"	/zeros/grandmaster "Y" /zeros/grandmaster "Y", "Z"
<i>Level in % (The word "Level" is optional within the string. It is not required but can be included to match the equivalent Playback level command). Optional fade time, in seconds</i>			
Blackout	/zeros/blackout/X		/zeros/blackout "X"
	<i>To turn Blackout on, X can = "1", "on", "enable", "enabled", or "true" To turn Blackout off, X can = "0", "off", "disable", "disabled", or "false"</i>		

Vision.Net




CAN



Function	iCANnet Cable Colours
0V	Black
CAN L	Blue
Shield	Silver
CAN H	White
+VDC	Red



Remote Switches



OSC



MIDI Timecode



MIDI Notes

